


12AT7/12AU7/12AX7/ECC81/ECC82/ECC83/ECC88/6922/6DJ8




- 1 = PlateA
- 2 = GridA
- 3 = CathodeA
- 4 = HeaterA
- 5 = HeaterB
- 6 = CathodeB
- 7 = GridB
- 8 = PlateB
- 9 = HeaterAB

Filament Voltage
 Filament Current
 Plate Voltage (*max*)
 Plate Current (*max*)
 Plate Dissipation (*max*)
 Screen Voltage (*max*)
 Screen Current (*max*)
 Screen Dissipation (*max*)

	12AT7/ECC81	12AU7/ECC82	12AX7/ECC83	ECC88/ 6922/ 6DJ8
Filament Voltage	6.3-12 V	6.3-12 V	6.3-12 V	6.3 V
Filament Current	150-30 mA	150-300mA	150-300mA	365 mA
Plate Voltage (<i>max</i>)	300 V	330 V	330 V	130 V
Plate Current (<i>max</i>)	15 mA	22 mA	6 mA	25 mA
Plate Dissipation (<i>max</i>)	2.5 W	3 W	1.1 W	1.8 W
Screen Voltage (<i>max</i>)	-- V	-- V	-- V	-- V
Screen Current (<i>max</i>)	-- A	-- A	-- A	-- A
Screen Dissipation (<i>max</i>)	-- W	-- W	-- W	-- W

6550/EL34




- 1 = GridC
- 2 = HeaterA
- 3 = Plate
- 4 = GridB
- 5 = GridA
- 6 = N/C
- 7 = HeaterB
- 8 = Cathode

Filament Voltage
 Filament Current
 Plate Voltage (*max*)
 Plate Current (*max*)
 Plate Dissipation (*max*)
 Screen Voltage (*max*)
 Screen Current (*max*)
 Screen Dissipation (*max*)

	6550	EL34
Filament Voltage	6.3 V	6.3 V
Filament Current	1.6 A	1.5 A
Plate Voltage (<i>max</i>)	800 V	800 V
Plate Current (<i>max</i>)	230 mA	140 mA
Plate Dissipation (<i>max</i>)	40 W	25 W
Screen Voltage (<i>max</i>)	600 V	425 V
Screen Current (<i>max</i>)	-- A	50 A
Screen Dissipation (<i>max</i>)	7 W	8 W

6L6/5881/KT66,77,88



- 1 = N/C
- 2 = HeaterA
- 3 = Plate
- 4 = GridB
- 5 = GridA
- 6 = N/C
- 7 = HeaterB
- 8 = Cathode

Filament Voltage
 Filament Current
 Plate Voltage (*max*)
 Plate Current (*max*)
 Plate Dissipation (*max*)
 Screen Voltage (*max*)
 Screen Current (*max*)
 Screen Dissipation (*max*)

	6L6/ 5881	KT66	KT77	KT88
Filament Voltage	6.3 V	6.3 V	6.3 V	6.3 V
Filament Current	0.9 A	1.3 A	1.5 A	1.6 A
Plate Voltage (<i>max</i>)	500 V	550 V	800 V	800 V
Plate Current (<i>max</i>)	140 mA	200 mA	140 mA	230 mA
Plate Dissipation (<i>max</i>)	30 W	25 W	25 W	40 W
Screen Voltage (<i>max</i>)	450 V	550 V	425 V	600 V
Screen Current (<i>max</i>)	35 mA	-- mA	50 mA	-- mA
Screen Dissipation (<i>max</i>)	5 W	3.5 W	8 W	7 W